

# Specifications



## Eaton 240695

Eaton Moeller series xComfort - Actuators.  
Switching device, all-pole

### General specifications

<b>PRODUCT NAME</b>	Eaton Moeller series xComfort switching actuator
<b>CATALOG NUMBER</b>	240695
<b>MODEL CODE</b>	CSAU-01/03
<b>EAN</b>	4015082406950
<b>PRODUCT LENGTH/DEPTH</b>	65 mm
<b>PRODUCT HEIGHT</b>	27 mm
<b>PRODUCT WIDTH</b>	65 mm
<b>PRODUCT WEIGHT</b>	0.084 kg
<b>COMPLIANCES</b>	RoHS conform
<b>GLOBAL CATALOG</b>	240695



Powering Business Worldwide

## Product specifications

<b>FEATURES</b>	Radio frequent bidirectional
<b>BUS SYSTEM OPERATING TYPE</b>	Radio frequent xComfort
<b>ACTUATION FUNCTION</b>	Switching
<b>BUS SYSTEM PRODUCT TYPE</b>	Actuator
<b>BUILT-IN INSTALLATION BOX DEPTH - MIN</b>	26 mm
<b>NUMBER OF INPUTS (BINARY)</b>	0
<b>NUMBER OF SWITCHING CONTACTS - MAX</b>	2
<b>RATED OPERATING VOLTAGE (UE) - MAX</b>	230 V
<b>RATED OPERATING VOLTAGE (UE) - MIN</b>	230 V
<b>AMPERAGE RATING</b>	8 A
<b>SWITCHING POWER LED - MAX</b>	0 W
<b>SWITCHING CURRENT - MAX</b>	6 A
<b>SWITCHING POWER - MAX</b>	1380 W
<b>WIDTH IN NUMBER OF MODULAR SPACINGS</b>	3
<b>OUTPUT POWER</b>	1380 W
<b>POWER SUPPLY</b>	Mains
<b>DEGREE OF PROTECTION</b>	IP20
<b>FUNCTIONS</b>	Bus module detachable
<b>MOUNTING METHOD</b>	Flush mounting Flush mounted (plaster)
<b>POWER CONSUMPTION</b>	0.6 W
<b>NUMBER OF LINKABLE DEVICES</b>	32

## Resources

DECLARATIONS OF CONFORMITY	<a href="#">eaton-switching-actuator-declaration-of-conformity-eu250184en.pdf</a>
DRAWINGS	<a href="#">eaton-xcomfort-xcomfort-sensor-dimensions-008.jpg</a>
INSTALLATION INSTRUCTIONS	<a href="#">IL136211064</a>
INSTALLATION VIDEOS	<a href="#">Pairing two or more switches to one actuator</a>
	<a href="#">xComfort - Pairing multiple switches with multiple actuators EN</a>
	<a href="#">xComfort - Pairing one switch with multiple actuators EN</a>
	<a href="#">xComfort - Pairing a double switch with two actuators EN</a>
	<a href="#">xComfort Sensors and Actuators Video EN-US</a>
	<a href="#">Pairing one switch to one actuator</a>
<a href="#">xComfort - Un-pairing a switch from an actuator EN</a>	
MANUALS AND USER GUIDES	<a href="#">DA-MN-136211064</a>
WIRING DIAGRAMS	<a href="#">eaton-wiring-diagram-csau_01_03.jpg</a>

---

**PROJECT NAME:**

**PROJECT NUMBER:**

**PREPARED BY:**

**DATE:**

---



**Eaton Corporation plc**  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

Follow us on social media to get the latest product and support information.



© 2025 Eaton. All Rights Reserved.