

# Specifications



Photo is representative

## Eaton 248287

Eaton Distribution parts. Shunt release (for power circuit breaker), 110-415V AC

### General specifications

<b>PRODUCT NAME</b>	Eaton Distribution parts
<b>CATALOG NUMBER</b>	248287
<b>MODEL CODE</b>	Z-ASA/230
<b>EAN</b>	4015082482879
<b>PRODUCT LENGTH/DEPTH</b>	80 mm
<b>PRODUCT HEIGHT</b>	75 mm
<b>PRODUCT WIDTH</b>	18 mm
<b>PRODUCT WEIGHT</b>	0.106 kg
<b>COMPLIANCES</b>	RoHS conform
<b>CERTIFICATIONS</b>	EN45545-2 IEC 61373
<b>GLOBAL CATALOG</b>	248287



Powering Business Worldwide

## Product specifications

<b>USED WITH</b>	Shunt releases Accessory for combined residual current/power circuit breaker Accessory Accessory for miniature circuit breaker
<b>ACCESSORY/SPARE PART TYPE</b>	Shunt release
<b>MOUNTING METHOD</b>	For fitting on left to: FAZ, FRBmM-1N, Z-MS
<b>ADDITIONAL EQUIPMENT REQUIRED</b>	Shunt release (for power circuit breaker)
<b>AMBIENT OPERATING TEMPERATURE - MAX</b>	75 °C
<b>AMBIENT OPERATING TEMPERATURE - MIN</b>	-35 °C
<b>ASSEMBLY WIDTH</b>	1 TE
<b>NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)</b>	0
<b>NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)</b>	1
<b>NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)</b>	1
<b>NUMBER OF POLES AT MAIN CONTACT UNIT - MAX</b>	1
<b>NUMBER OF SWITCHES (FAULT SIGNAL)</b>	0
<b>VOLTAGE TYPE</b>	AC
<b>FUNCTIONS</b>	Shunt release (for power circuit breaker)
<b>DEVICE FITTING</b>	Other
<b>TYPE</b>	<ul style="list-style-type: none"> <li>• Accessory</li> <li>• Accessory for combined residual current/power circuit breaker</li> <li>• Accessory for miniature circuit breaker</li> </ul>
<b>APPLICATION</b>	Switchgear for industrial and advanced commercial applications
<b>RATED OPERATIONAL VOLTAGE (UE) - MAX</b>	415 V

## Resources

DECLARATIONS OF CONFORMITY	<a href="#">eaton-distribution-parts-declaration-of-conformity-eu250433en.pdf</a>
DRAWINGS	<a href="#">eaton-dimensions-mas-asa.eps</a>
ECAD MODEL	<a href="#">ETN.Z-ASA 230.edz</a>
INSTALLATION INSTRUCTIONS	<a href="#">IL019165ZU</a>
WIRING DIAGRAMS	<a href="#">eaton-wiring-diagram-asa.jpg</a>

---

**RATED SWITCH CURRENT** 0 A

**SUITABLE FOR CURRENT  
OF MAIN CONTACT UNIT  
- MAX** 15 A

---

---

**PROJECT NAME:**

**PROJECT NUMBER:**

**PREPARED BY:**

**DATE:**

---



**Eaton Corporation plc**  
Eaton House  
30 Pembroke Road  
Dublin 4, Ireland  
Eaton.com

Follow us on social media to get the latest product and support information.



© 2025 Eaton. All Rights Reserved.