

PS EFI - MD



Specificatii

Cod ETI	002069001
Descriere	PS EFI - MD
Denumire clasă	Comutator auxiliar
Func ie	Contact auxiliar
Curent nominal (A)	6
Tensiunea nominală(V)	230
Utilizare cu	EFI (16-80 A)
Număr de contacte NC	1
Frecven ă nominală (Hz)	50/60
Standarde	EN 62019
Sec iune transversală nominală	1-2.5
Număr contacte NO	1

[Pagina de produse online](#)

Alta documentatie

[Catalog caracteristici tehnice](#)

[Model 3D](#)

[Manual de instructiuni](#)

[Declaratie CE](#)

[COM_ETISTORE_ITEM_DOCTYPE_whitePa
per](#)

[Eplan mușchi](#)

ETIM clasificare internationala

Clasificare	EC001286
Denumire clasă	Auxiliary device for distribution board devices
Device fitting	Earth leakage switch
Additional equipment	Auxiliary switch
Assembly width (in number of modular spacings)	0,5
Number of contacts as normally open contact	1
Number of contacts as normally closed contact	1
Rated switch current	6A
Rated voltage	230V
Voltage type for actuating	AC
Suitable for max. number of poles main contact unit (total)	4
Suitable for max. current main contact unit	80A

Desen cotat

